Setup WIFI - WorkAboutPro Pro2 and Pro3 scanners

Types of scanner



Setup Wifi



Select SCU in the Windows dropdown menu

📃 MyMobiler					×		
File Edit View	Tools						
] 🖩 🚜 🕩 🛍	🖥 🖫 🖷 🔎 🏷	>					
Summit Client Utility 💦 👫 📢 ok							
Edit Profile:	uest		•	SDC			
New	Rename	Dele	ete	Scan			
Radio:							
SSID		quest					
Client Nar	ne 📃	5					
Power Sav	ve 🗖						
Tx Power	-						
Encryption	Encryption:			EAP Type:			
WPA2-PS	None 🔻						
WEP keys/PSKs		Credentials					
Save Changes:			Comm	it			
Mair Pro	file Status	Diags	Global				

In the Profile tab, click on the Scan button

MyMobiler			×
<u>File E</u> dit View <u>T</u> ools			
] 🖩 🔏 🗅 🛍 🖥 🖷 🖷 🥥 🏷			
Summit Client Utili	ity	#‡ €€	ok
SSID	RSSI	Secure	
HHF-VLAN	-59	true	
4G-internet	-79	true	
HAVNECAFEEN	-81	true	
tolderstien2	-88	true	
Configure		Refresh	

Select the WIFI network to be added and click on the *Configure* button



Click on the Yes button



Enter password.



Click on the OK button

📃 MyMobiler						
File Edit Vi	ew Tools					
] 🖩 🚜 🐚 🕻	à 🖥 🖫 🖷	ଚ୍ଚ 🏷				
ಶ Sun	nmit Clien	t Ut	ility	÷	≵ •€	ok
Edit Profile: [HHF-VLAI	N		•	SD	C
New	Renar	ne	Dele	ete	Scan	l I
Radio:						
SSID			HHF-\	/LAN		
Client Na	ame	=				
Power S	ave					
Tx Powe	er	\bullet				
Encryptic	Encryption: EAP Type:					
WPA-PSK 🔻			None 🔻			
WEP keys/PSKs Credentials						
Save Changes: Commit						
Main Pr	ofile Stat	us	Diags	Globa	al	

Save the profile by clicking the *Commit* button

ĺ	📃 MyMobi	iler						x	
	File Edi	it View	Tools						
	🤊 (S	Summ	, u	# 4€	ok				
	Edit Profile	e: HF	IF-VLAN			•	SDO	C	
	Ne	w	Renam	ne	Dele	te	Scan		
	Radio	:							
	SSID				HHF-VLAN				
	Client	Nam	e i	=]	
	Powe	r Save	e i						
	Tx Power			•					
	Encry	ption:			EAP Type:				
	WPA-PSK 👻			▼	None 🔻				
	WEP keys/PSKs Save Changes:			Credentials					
					Comr	nit			
$\left(\right)$	Main	rofil	e Statu	IS	Diags	Globa	al		

Select the Main tab

📃 MyMobiler				- • ×	1
File Edit View Tools					
] 🖩 🔏 🗅 🏠 🖥 🖷	🖫 🔁 🏷				
🍠 Summit C	lient Uti	ility	2 :•	€ ok	\triangleright
	•				
		Dis	sable R	adio	
Active Profile:	HHF-VL	AN		-	\triangleright
Status: Radio Type:	ThirdPa Default guest	rtyCor	fig		
Reg. Domain:	HHF-VL	AN			
Auto Profile:	<mark>⊖</mark> On		Off	List	
Driver: v3.02.	09 9	SCU: \	/3.02.09)	
		A	bout S	CU	
Main Duefile	Charteria	D:	Clabel		
	Status	Diags	Global		_
		H			

Select the new profile as *Active Profile*

In order to end the WIFI setup, click on the **OK** button in the upper left corner of the screen and restart the scanner

- **Pro2**: Pres and hold down the buttons *FN-Enter-FN* in about 5 seconds
- Pro3: Press and hold down the buttons FN-F4-PowerOn/Off in about 5 seconds



Enter Username and Password and then click OK